

# **PIN Code Setting for Acme**

Version 2.0





## Copyright & Trademarks

The Virbox, Virbox Elite 5, Virbox EL5 Acme, Virbox Cloud LM with its technical documentation is copyrighted to present by ©Beijing SenseShield Technology Co., Ltd (SenseShield). All rights reserved.

The **Virbox**, **Virbox LM**, **Virbox Protector**, **Virbox Elite 5**, **Virbox EL5 Acme** are registered Trademarks of **SenseShield** in China and other countries.

All products referenced throughout this document are trademarks of their respective owners.

## Disclaimer

All attempts have been made to make the information in this document complete and accurate. But we cannot guarantee everything is perfect, we will correct it in next version released in case some error has been found. SenseShield is not responsible for any direct or indirect damages or loss of business resulted from inaccuracies or omissions.

The specifications contained in this document are subject to change without notice.

## Documentation Improvement

Any suggestion to this manual from you are welcome, We are glad to hear any feedback from you which will help us to continuously improve the documents quality and support and serve the developer to protect software products more efficiently.

## Contact

Company: Beijing SenseShield Technology Co., Ltd

Address: Suite 510, Block C, Internet Innovation Center, Building 5, No.10, Xibeiwang East Road, Haidian District, Beijing China

Tel.: +86-10-56730936

Fax: +86-10-56730936-8007

Sales: info@senselock.com;

Website: <https://lm-global.virbox.com/>



---

## Table of Content

1. PIN Code introduction .....	3
2. PIN Code Configuration Process .....	3
3. PIN Code Verification in Virbox Developer Utility and Virbox Protector .....	7


# 1. PIN Code introduction


Senseshield added PIN Code verification to EL5 Acme **Master Lock**, which intention is to prevent unauthorized people issue the license of the Protected Software use master Lock. And at the same time if the Lock is lost, to protect the software maximumly.

**Note:** Software developer need to keep your PIN code (password) safe. If you have lost the PIN you can't get back the PIN code, and have to buy dongle again.

# 2. PIN Code Configuration (Modify) Process


- Login the Virbox Developer Center. In the Virbox Developer Center you can get the initial PIN code of the Master Lock.






Here you can get the PIN code of the Hardware Lock, please keep good record of the PIN Code.

- Download SDK and install in your computer. Modify PIN code.




After you have installed SDK in your computer, please open the Virbox Developer Utility. Here take windows 10 as an example,




Open PIN setting of Virbox Developer Utility to modify PIN code.

- ◆ Insert the Master Lock to your computer, Click “**Master PIN Lock Settings**”.




The PIN setting window will popup, please click “**Change PIN**”.



“Original PIN” is the PIN Code you get from the **Virbox Developer Center**, “New PIN” and “Confirm PIN” is the PIN Code after modification, after input all of the information and click “Confirm” to save the modification.


For security issue, please modify the initial PIN to a new PIN.




So far, we have completed the modification of the PIN Code, we need to verify it in next step.


### 3. PIN Code Verification in Virbox Developer Utility and Virbox Protector

- Verify PIN code in **Virbox Developer Utility**, click **"Verify PIN Now"**,



Input window will popup, please input the new PIN Code and click **"Confirm"**.






It shows “**Verify PIN successfully**”, now we have finished the PIN Code verification in Virbox Developer Utility.

■ Verification in **Virbox Protector**.


Please Exit the Virbox Developer Utility first.

**Note:** Software Developer need to keep the New PIN code in mind, if it is lost, you can't get the PIN code back, and every time when Software Developer want to issue License, you need verify the PIN Code.


Open Virbox Protector,



Click "Verify PIN",




PIN Verify window will popup,



Input the PIN code you just modified in Virbox Developer Utility and click "Verify".

The status of PIN code will show in the blow picture.



**Note:** Both **Virbox Developer Utility** and **Virbox Protector** can recognize Master Dongle, so you'd better keep only the one software you will use is opened, and the other one is closed, to avoid the conflict of the two software.